

OxyLED Wireless Motion Sensor LED Light

Model: T-02U

User Manual

Description

Using both infrared (PIR) technology to detect body heat and the human motion sensor (within 3m), the OxyLED T-02U Wireless Motion Sensor Light turns on or off based on occupancy and ambient light levels. It is designed to substitute a standard light switch and built for convenience and personal safety in dark areas. It has a built-in rechargeable battery via micro USB cable. It is ideal for corridors, cabinets, workshops, basements, indoor garages, stairwells, doorways, closets, and other dark places in your home and shed.

Features

- 20 super bright LEDs: Contains 20 energy-saving LEDs to illuminate dark spaces.
- Motion activated: Automatically senses human motion within 3 metres and turns off 15 seconds after you walk away from sensing range
- USB charging : Built-in rechargeable batteries. No electric wire, no need to replace batteries.
- 3 working modes: OFF/ON/Auto Switch. AUTO for motion-sensitive mode. ON for constant on mode
- Simple installation: The adhesive strip with magnetic fields is easily attached to and detachable from the lamp body for convenient installation.
- Application: bedroom, hallway, washroom, balcony, corridor, stair, attic, the basement, garage, cellar, wardrobe, hotel ambry, kitchen cupboards, bookcase, tents etc.

Specifications

- Sensitivity: 3m/10ft
- Sensor range: 120 degrees
- LED quantity: 20 LEDs
- Light color: white
- LED life: 50,000 hours or more
- Battery: built-in 3.7V/700mAh lithium battery
- Size: 180x30 mm / 7.1x1.18 in (L x W)
- Material: aluminum + ABS

- Weight: 112g/3.95oz

Operation

1. Charging

- Charge your T-02U light with supplied cable or other Micro USB cable.
- Connect it to any 5V USB port such as power adapter, power bank, computer USB port etc.

LED indicator lights on red during charging process while lights on blue after being fully charged.

2. Installation

a. Mount by adhesive magnetic strip

- Choose a smooth and dry position that you want to mount. If not, please clean it before sticking.
- Peel down the brown surface of 3M adhesive strip and then stick it on the ideal position chosen.

b. Mount by supplied screws

This device is supplied with 3 screws for extra installation.

3. Choose Lighting Mode

The OFF/ON/Auto Switch locates at one side of light(Auto mode recommended).

OFF- never lights on

ON- constantly on

Auto – lights on when people get close to its sensing range at darkness while lights off when they step away from it 15s later

Note:

- This motion sensor night light won't light up during daytime when it is bright enough.
- Don't put 2pcs of this light too close. The light of one may cause the other not light up if they are too close.

Package Contents

1 x OxyLED T-02U Motion Sensor Night Light

1 x Micro USB Cable

3 x Screw

1 x User Manual

1 x Warranty Card